

# Fuji Ceramic Surge Absorbers

ENC series ENE series

Nov-01

## Types and characteristics

varistor voltage	Maximum rating Applied voltage		Peak current (8/20us) Amps.						
	Volts ACrms	Volts DCrm							
22(20 to 24)	14	18	ENC220D-05B	ENC220D-07B	ENC220D-10B				ENC220D-14B
27(24 to 30)	17	22	ENC270D-05B	ENC270D-07B	ENC270D-10B				ENC270D-14B
33(30 to 36)	20	26	ENC330D-05B	ENC330D-07B	ENC330D-10B				ENC330D-14B
39(35 to 43)	25	31	ENC390D-05B	ENC390D-07B	ENC390D-10B				ENC390D-14B
47(42 to 52)	30	38	ENC470D-05B	ENC470D-07B	ENC470D-10B				ENC470D-14B
56(50 to 62)	35	45	ENC560D-05B	ENC560D-07B	ENC560D-10B				ENC560D-14B
68(61 to 75)	40	56	ENC680D-05B	ENC680D-07B	ENC680D-10B				ENC680D-14B
82(74 to 90)	50	65		ENC820D-05A		ENC820D-07A	ENE820D-05A		ENC820D-10A
100(90 to 110)	60	85		ENC101D-05A		ENC101D-07A	ENE101D-05A		ENC101D-10A
120(108 to 132)	75	100		ENC121D-05A		ENC121D-07A	ENE121D-05A		ENC121D-10A
150(135 to 165)	95	125		ENC151D-05A		ENC151D-07A	ENE151D-05A		ENC151D-10A
200(185 to 225)	130	170		ENC201D-05A		ENC201D-07A	ENE201D-05A		ENC201D-10A
220(198 to 242)	140	180		ENC221D-05A		ENC221D-07A	ENE221D-05A		ENC221D-10A
240(216 to 264)	150	200		ENC241D-05A		ENC241D-07A	ENE241D-05A		ENC241D-10A
270(247 to 303)	175	225		ENC271D-05A		ENC271D-07A	ENE271D-05A		ENC271D-10A
360(324 to 396)	230	300		ENC361D-05A		ENC361D-07A	ENE361D-05A		ENC361D-10A
390(351 to 429)	250	320		ENC391D-05A		ENC391D-07A	ENE391D-05A		ENC391D-10A
430(387 to 473)	275	350		ENC431D-05A		ENC431D-07A	ENE431D-05A		ENC431D-10A
470(423 to 517)	300	385		ENC471D-05A		ENC471D-07A	ENE471D-05A		ENC471D-10A
620(558 to 682)	385	505							ENC621D-10A
680(612 to 748)	420	560							ENC681D-10A
750(675 to 825)	460	615							ENC751D-10A
780(702 to 858)	485	640							ENC781D-10A
820(738 to 902)	510	670							ENC821D-10A
910(819 to 1001)	550	745							ENC911D-10A
1000(900 to 1100)	625	825							ENC102D-10A
1100(990 to 1210)	680	895							ENC112D-10A
1800(1620 to 1980)	1000	1465							

varistor voltage	Maximum rating Applied voltage		Peak current (8/20us) Amps.						
	Volts ACrms	Volts DCrm							
22(20 to 24)	14	18		ENC220D-20B					
27(24 to 30)	17	22		ENC270D-20B					
33(30 to 36)	20	26		ENC330D-20B					
39(35 to 43)	25	31		ENC390D-20B					
47(42 to 52)	30	38		ENC470D-20B					
56(50 to 62)	35	45		ENC560D-20B					
68(61 to 75)	40	56		ENC680D-20B					
82(74 to 90)	50	65	ENE820D-07A		ENC820D-14A	ENE820D-10A	ENC820D-20A	ENE820D-14A	ENE820D-20A
100(90 to 110)	60	85	ENE101D-07A		ENC101D-14A	ENE101D-10A	ENC101D-20A	ENE101D-14A	ENE101D-20A
120(108 to 132)	75	100	ENE121D-07A		ENC121D-14A	ENE121D-10A	ENC121D-20A	ENE121D-14A	ENE121D-20A
150(135 to 165)	95	125	ENE151D-07A		ENC151D-14A	ENE151D-10A	ENC151D-20A	ENE151D-14A	ENE151D-20A
200(185 to 225)	130	170	ENE201D-07A		ENC201D-14A	ENE201D-10A	ENC201D-20A	ENE201D-14A	ENE201D-20A
220(198 to 242)	140	180	ENE221D-07A		ENC221D-14A ENC221K-14A ENC221C-14A	ENE221D-10A	ENC221D-20A	ENE221D-14A	ENE221D-20A
240(216 to 264)	150	200	ENE241D-07A		ENC241D-14A	ENE241D-10A	ENC241D-20A	ENE241D-14A	ENE241D-20A
270(247 to 303)	175	225	ENE271D-07A		ENC271D-14A ENC271K-14A ENC271C-14A	ENE271D-10A	ENC271D-20A	ENE271D-14A	ENE271D-20A
360(324 to 396)	230	300	ENE361D-07A		ENC361D-14A	ENE361D-10A	ENC361D-20A	ENE361D-14A	ENE361D-20A
390(351 to 429)	250	320	ENE391D-07A		ENC391D-14A ENC391K-14A ENC391C-14A	ENE391D-10A	ENC391D-20A	ENE391D-14A	ENE391D-20A
430(387 to 473)	275	350	ENE431D-07A		ENC431D-14A	ENE431D-10A	ENC431D-20A	ENE431D-14A	ENE431D-20A
470(423 to 517)	300	385	ENE471D-07A		ENC471D-14A ENC471K-14A ENC471C-14A	ENE471D-10A	ENC471D-20A	ENE471D-14A	ENE471D-20A
620(558 to 682)	385	505			ENC621D-14A	ENE621D-10A	ENC621D-20A	ENE621D-14A	ENE621D-20A
680(612 to 748)	420	560			ENC681D-14A	ENE681D-10A	ENC681D-20A	ENE681D-14A	ENE681D-20A
750(675 to 825)	460	615			ENC751D-14A	ENE751D-10A	ENC751D-20A	ENE751D-14A	ENE751D-20A
780(702 to 858)	485	640			ENC781D-14A	ENE781D-10A	ENC781D-20A	ENE781D-14A	ENE781D-20A
820(738 to 902)	510	670			ENC821D-14A	ENE821D-10A	ENC821D-20A	ENE821D-14A	ENE821D-20A
910(819 to 1001)	550	745			ENC911D-14A	ENE911D-10A	ENC911D-20A	ENE911D-14A	ENE911D-20A
1000(900 to 1100)	625	825			ENC102D-14A	ENE102D-10A	ENC102D-20A	ENE102D-14A	ENE102D-20A
1100(990 to 1210)	680	895			ENC112D-14A	ENE112D-10A	ENC112D-20A	ENE112D-14A	ENE112D-20A
1800(1620 to 1980)	1000	1465			ENC182D-14A	ENE182D-10A	ENC182D-20A	ENE182D-14A	